

Model No.

LV-50S-RM

Potentiometer Volume Control

INCLUDES:

- Potentiometer volume control
- Adhesive label with printed dial scale
- Rotary knob



POTENTIOMETER VOLUME CONTROL with 50 ohm impedance provides economical volume level adjustment in systems with low power circuits. This unit includes an adhesive label with printed dial scale and black rotary knob.

FEATURES

DESCRIPTION: Potentiometer volume control for use with 4, 8, or 16 ohm voice coil circuits

RESISTANCE: 50 ohm

POWER RATING: 5W audio

SWITCH TYPE: Rotary knob, black

ATTENUATION: Continuous attenuation with stops at minimum and maximum

ADHESIVE LABEL: Black label with white printed dial scale and plastic window to insert a paper label.

COUNTRY OF ORIGIN: Assembled in U.S.A. (Chinese components)

A&E SPECIFICATIONS

The potentiometer volume control with 50 ohm impedance shall be Lowell model LV-50S-RM, which shall feature continuous attenuation with stops at minimum and maximum. It shall include a black adhesive label with printed dial scale (Off-10), black rotary knob, and mounting screws.

LV SERIES OVERVIEW

Model No.	Power Rating	Resistance	Steps	Switch Type	Style	Color	For Use With
LV-50S	5W audio	50 ohm	continuous	rotary knob	1g standard wall plate	ss	voice coil circuits
LV-50S-RM	5W audio	50 ohm	continuous	rotary knob	adhesive label	black	voice coil circuits
LV-5K	5W audio	5k ohm	continuous	rotary knob	1g standard wall plate	ss	25/70V speaker line

THIS SPEC

DRAWINGS

