

LOWELL MANUFACTURING CABINET & RACK SEISMIC QUALIFICATION SUMMARY CABINET AND ANCHORAGE INSTALLATION DETAILS

CALIFORNIA BUILDING CODE SEISMIC CERTIFICATION FOR USE IN ESSENTIAL FACILITIES & SEISMIC APPLICATIONS

Client:

Lowell Manufacturing Company 100 Integram Drive Pacific, Missouri 63069 (636) 257-3400 (636) 257-6606 FAX www.lowellmfg.com

By:

CCS Group, Inc. 1415 Elbridge Payne Rd., Suite 265 Chesterfield, MO 63017 (636) 532-2100

May 2011

CCS Project #: CCS10-050



5-2-11



			-	S	HEET NO) 1
JOB NO.	CCS10-050	JOB	Lowell Manufacturing	BY_	CMS	DATE 5/2/2011
CALC. NO.		SUBJECT	Seismic Certification.	CHK'D	MJG	DATE 5/2/2011

TABLE OF CONTENTS

			<u>PAGE</u>
1.	Purpose		1
2.	Summary	1	2
3.	Referenc	es	6
4.	Design C	riteria	*
5.	Seismic (Certification of Racks & Cabinets	*
	5.1.	Model LSGR-4422 & LSER-4422 Qualification	*
	5.2.	Model LSGR-4022 & LSER-4022 Qualification	*
	5.3.	Model LSGR-3522 & LSER-3522 Qualification	*
	5.4.	Model LSGR-4427, -4432, -4436, & LSER-4427, -4432	*
	5.5.	Model LSGR -4027, -4032, -4036, & LSER-4027, -4032	*
	5.6.	Model LSGR-3527, -3532, -3536 & LSER-3527, -3532	*
	5.7.	Model LSGR-2427 & LSER-2422, -2427, -2122, -2127	*
6.	Anchorag	ge	*
	6.1.	Life-Safety/Essential Systems (Rack & Cabinet + Anchorage)	*
	6.2.	Typical Installations (Anchorage only)	*
Appendi	ces:		
Appendix	Α	Lowell CBC Seismic-Certified Installation Details	7
Appendix	В	Lowell Cabinet and Rack Assembly Drawings	*

 * Not included in package – see Seismic Qualification Calculations Package

dated May 2011, CCS Project No. CCS10-050

5-2-11



ccs aroup, inc	. • Creative Col	ISTRUCTION SOLUTION	JIIS		S	HEET NO) 1	
JOB NO.	CCS10-050	JOB	Lowell Manufacturing		BY	CMS	DATE	5/2/2011
CALC. NO.		SUBJECT	Seismic Certification.	C	HK'D	MJG	DATE	5/2/2011

1.0 PURPOSE:

The purpose of this calculation is to document the seismic qualification and certification of selected Lowell Manufacturing equipment racks and cabinets used to support electronic components to the seismic criteria of the 2010 California Building Code. Specifically, this package provides seismic qualification and certification requirements for two (2) categories of seismic qualification:

- 1. Racks and cabinets identified as part of a Life Safety/Essential System. These cabinets and racks are so designated and required in critical or essential facilities where operation and function following a major earthquake event is necessary (Ip = 1.5).
- 2. Racks and cabinets requiring seismic design by code (Ip = 1.0), but are NOT identified as a Life Safety/Essential System. These racks and cabinets only require their supports and attachments; i.e., anchorage, to be seismically qualified and certified.

The 2010 California Building Code (CBC), Title 24 regulations references and relies on the 2009 IBC and ASCE/SEI 7-05 for the applicable seismic design provisions for nonstructural components. The 2009 International Building Code (IBC) seismic design requirements were used to seismically qualify the selected Lowell electronic equipment racks and cabinets. The 2009 IBC also references the American Society of Engineers Standard ASCE/SEI 7-05 for the applicable seismic design provisions for nonstructural components; thus the qualification of the Lowell racks and cabinets herein are code compliant with the seismic design provisions of both the 2009 IBC and 2010 CBC.

This seismic qualification package contains the seismic analysis supporting the seismic qualification of the listed Lowell Manufacturing equipment racks and cabinets. In addition, the resulting installation instructions were developed for the equipment racks, cabinets, and their anchorage systems based on the results of seismic calculations and limits established by the IBC seismic provisions. These seismic qualification and installation instructions are organized to establish the maximum spectral accelerations (Ss) for the selected racks and cabinets. Specific cabinet and rack details are included for various spectral accelerations associated with differing seismic regions and location within the building structure (basement to roof). Anchorage instructions for the qualified cabinets including anchor size, type, embedment, spacing, and edge distance requirements are also developed and provided.



JOB NO.	CCS10-050	JOB	Lowell Manufacturing	BY_	CMS		5/2/2011
CALC. NO.		SUBJECT	Seismic Certification.	CHK'D	MJG	DATE	5/2/2011

SHEET NO 2

2.0 **SUMMARY**:

The following Lowell Manufacturing rack and cabinet models meet or exceed the seismic design requirements as specified in the 2009 International Building Code, Section 1613 and the 2010 California Building Code, Section 1613.

Life Safety/Essential Systems (Ip = 1.5) -

Cabinet Models:

 LSER-2122, LSER-2422, LSER-3522, LSER-4022, LSER-4422, LSER -2127, LSER-2427, LSER-3527, LSER-4027, LSER-4427, LSER-3532, LSER-4032, LSER-4432.

Ganging Rack Models:

 LSGR-3522, LSGR-4022, LSGR-4422, LSGR-2427, LSGR-3527, LSGR-4027, LSGR-4427, LSGR-3532, LSGR-4032, LSGR-4432, LSGR-4036, and LSGR-4436.

Typical Installations (Anchorage only, Ip = 1.0) -

Cabinet Models:

 LSER-2122, LSER-2422, LSER-3522, LSER-4022, LSER-4422, LSER -2127, LSER-2427, LSER-3527, LSER-4027, LSER-4427, LSER-3532, LSER-4032, LSER-4432.

Ganging Rack Models:

 LSGR-3522, LSGR-4022, LSGR-4422, LSGR-2427, LSGR-3527, LSGR-4027, LSGR-4427, LSGR-3532, LSGR-4032, LSGR-4432, LSGR-4036, and LSGR-4436.


Fixed Rail Cabinet Models:

LSER-F2122, LSER-F2422, LSER-F3522, LSER-F4022, LSER-F4422, LSER-F2127, LSER-F2427, LSER-F3527, LSER-F4027, and LSER-F4427.

The cabinets and racks shall be installed in accordance with the seismic instructions included herein as Appendix A. Figures 1a, 1b, and 1c provide a summary of the seismic qualification for the applicable Life Safety/Essential Systems cabinet/rack models vs. spectral acceleration, S_s . Table 3a, 3b, and 3c on sheets S1.3a, S1.3b, and S1.3c in Appendix A provide the detailed seismic qualification with respect to the maximum spectral acceleration (Ss) for the respective cabinet series and model in this category (Ip = 1.5).



JOB NO. CCS10-050 JOB			ions	SHEET NO 3				
JOB NO.	CCS10-050	JOB _	Lowell Manufacturing	BY_	CMS	DATE	5/2/2011	
CALC. NO.		SUBJECT	Seismic Certification.	CHK'D	MJG	DATE	5/2/2011	




Note 1. Qualification based on the specified loading used in the calculations.

Figure 1a: Qualification for Lowell Manufacturing's LSGR-XX22, LSGR-XX27, LSGR-XX32, & LSGR-XX36 Rack Series and LSER-XX22, LSER-XX27, & LSER-XX32 Cabinet Series



CCS Group, Inc	. • Creative Cor	istruction Solut	tions	SHEET NO4				
JOB NO.	CCS10-050	JOB	Lowell Manufacturing		BY	CMS	DATE	5/2/2011
CALC. NO.		SUBJECT	Seismic Certification.	(CHK'D	MJG	DATE	5/2/2011




Note 1. Qualification based on the specified loading used in the calculations.

Figure 1b: Qualification for Lowell Manufacturing's LSGR-XX22, LSGR-XX27, LSGR-XX32, & LSGR-XX36 Rack Series and LSER-XX22, LSER-XX27, & LSER-XX32 Cabinet Series



		ions	5	SHEET NO 5				
JOB NO.	CCS10-050	JOB _	Lowell Manufacturing	BY_	CMS	DATE	5/2/2011	
CALC. NO.		SUBJECT	Seismic Certification.	CHK'D	MJG	DATE	5/2/2011	



Note 1. Qualification based on the specified loading used in the calculations.

Figure 1c: Qualification for Lowell Manufacturing's LSGR-XX22, LSGR-XX27, LSGR-XX32, & LSGR-XX36 Rack Series and LSER-XX22, LSER-XX27, & LSER-XX32 Cabinet Series



		tions		SHEET NO 6				
JOB NO.	CCS10-050	JOB	Lowell Manufacturing	BY	CMS	DATE	5/2/2011	
CALC. NO.		SUBJECT	Seismic Certification.	CHK'D	MJG	DATE	5/2/2011	

3.0 REFERENCES:

- 1. American Concrete Institute "ACI 318-08 Building Code Requirements for Structural Concrete and Commentary" Second Printing, June 2008.
- 2. American Institute of Steel Construction, "Steel Construction Manual," Thirteenth Edition, 2005.
- 3. California Building Standards Commission, "2010 California Building Code, California Code of Regulations Title 24. 1st Printing, June 2010.
- 4. Computers and Structures, Inc., "ETABS Plus" Software Version 9.7.0, 1984-2010.
- 5. ICC Evaluation Service, "ICC-ES Evaluation Report ESR-1917" 2007.
- 6. ICC Evaluation Service, "ICC-ES Evaluation Report ESR-1771" 2008.
- 7. ICC Evaluation Service "ICC-ES Evaluation Report ESR-2502", 2010.
- 8. International Code Council, Inc., "International Building Code 2006 Edition" 2nd Printing November 2006.
- 9. International Code Council, Inc., "International Building Code 2009 Edition" 1st Printing February 2009.
- 10. Lowell Manufacturing Company, Product Specification Sheets
 - LSER-44XX and LSGR-44XX Series Specification Sheet 01-2920, 06-15-10
 - LSER-40XX and LSGR-40XX Series Specification Sheet 01-2921, 06-15-10
 - LSER-35XX and LSGR-35XX Series Specification Sheet 01-2922, 06-15-10
 - LSER-24XX and LSGR-24XX Series Specification Sheet 01-2923, 06-15-10
- 11. RSG Software Inc., "CFS" Software Version 6.0.2" 1988-2009.
- 12. SEI/ASCE 7-05, "ASCE Standard Minimum Design Loads for Buildings and Other Structures," American Society of Civil Engineers, 2006.



				3	PHEFIN	<i></i>	
JOB NO.	CCS10-050	JOB	Lowell Manufacturing	BY	CMS	DATE	5/2/2011
CALC. NO.		SUBJECT	Seismic Certification.	CHK'D	MJG	DATE	5/2/2011

APPENDIX A

CBC Seismic-Certified Installation Details

(30 pages excluding this cover)

GENERAL NOTES

- 1. Lowell Manufacturing model applicability:
 - LSGR-XX22, LSGR-XX27, LSGR-XX32, & LSGR-XX36 series 19" ganging racks with seismic base. Ref. specific model loads in Table I & 2 below.
 - LSER-XX22, LSER-XX27, & LSER-XX32 series | 19" stand alone cabinets with seismic base. Ref. specific model loads in Table | \$ 2 below.
- Design Criteria: The 2010 California Building Code (CBC), section 1613
 - Spectral Response Acceleration, Ss = from 2010 California Building Code (2010 CBC Figure 1613.5(1))
 - Site Class A, B, C or D. Qualification instructions not applicable to site class E & F sites.
 - Importance Factor, Ip = 1.5 (Life Safety /Essential Systems) Ip = 1.0 (Standard installations - anchorage only)
 - Equation 13.3-1 (ASCE 7-05)

$$F_{p} = \frac{O.4 \text{ ap } S_{DS} \text{ Wp}}{R_{p}/I_{p}} \left[1 + 2 \frac{z}{h} \right] \qquad F_{pmin} = 0.3 \text{ S}_{DS} I_{p} \text{ Wp} \qquad F_{pmax} = 1.6 \text{ S}_{DS} I_{p} \text{ Wp}$$

- f. Cabinet supported on Normal or Light Weight Concrete with f'c=3000 psi mi
- q. Maximum weight, cabinet and contents:

Table | Life Safety /Essential Systems (Ip = 1.5)

Models	MP	CONTENT WEIGHT
LSGR-4421, LSGR-4432, LSGR-4436, LSER-4421, LSER-4432	1,200 lb	980 lb
L9GR-4027, L9GR-3527, L9GR-4032, L9GR-3532, L9GR-4036, L9GR-3536, L9GR-4027, L9GR-3527, L9GR-4032, L9GR-3532	l,100 lb	900 lb
L9GR-4422, L9GR-4022, L9GR-3522, L9ER-4422, L9ER-4022, L9ER-3522	900 lb	725 lb
LSER-2122, LSER-2121, LSGR-2421, LSER-2422, LSER-2427	600 lb	500 lb

Maximum attachment loads at anchorage to building structure (per anchor):

Max. tension = 665 lb Max. shear = 225 lb



5-2-11

LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-FXX22, LSER-FXX27, LSER-XX22, LSER-XX27, & LSER-XX32 SEISMIC (-S) CABINET/RACK - CBC



100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



JOB NO. CCS10-050 DATE 2 MAY 2011

415 Elbridge Payne Rd Sulte 265 Chesterfield, MO 63017 MO COA # 2006012564

GENERAL NOTES CONT'D

Table 2 Typical Installations Anchorage Only (Ip = 1.0)

Models	WP	CONTENT WEIGHT
LSGR-4427, LSGR-4432, LSGR-4436, LSER-4427, LSER-4432		
LSGR-4027, LSGR-3527, LSGR-4032, LSGR-3532, LSGR-4036, LSGR-3536,		
LSER-4027, LSER-3527, LSER-4032, LSER-3532		
LSGR-4422, LSGR-4022, LSGR-3522, LSER-4422, LSER-4022, LSER-3522	1,500 lb	1,200 lb
LSER-2122, LSER-2127, LSGR-2427, LSER-2422, LSER-2427		
LSER-F1422, LSER-1422, LSGR-2122, LSGR-2422		
LSER-F2122, LSER-F2422, LSER-F3522, LSER-F4022, LSER-F4422		
LSER-F2127, LSER-F2427, LSER-F3527, LSER-F4027, LSER-F4427		

Maximum attachment loads at anchorage to building structure (per anchor):

Max. tension = 1,516 lbMax. shear = 360 lb

3. Installation Instructions:

- a. Select desired cabinet or rack model. Verify content weight is not exceeded per Table 1 for Life Safety/Essential Systems (Ip = 1.5) or Table 2 for Standard Installations (Ip = 1.0).
- Determine The Spectral Response Acceleration, $5_{\rm s}$ at short periods -0.2 sec. from:
 - 2010 CBC Figure 1613.5(1)
 - Contact Lowell
- c. Determine Soil Site Class and verify if A, B, C or D. Qualification instructions not applicable to site class E & F sites. Site Class for the building site may be obtained from:
 - Building Structural Design Drawings
 - Geotechnical Report or Engineer
- d. Verify Importance Factor

(lp = 1.5 for life safety/essential systems)

(lp = 1.0 for standard installations-anchorage only)



5-2-11

LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-FXX22, LSER-FXX27, LSER-XX22, LSER-XX27, & LSER-XX32 SEISMIC (-S) CABINET/RACK - CBC



100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



JOB NO. CCS10-050 DATE 2 MAY 2011 S1.1

GENERAL NOTES CONT'D

- e. Determine Location in Bldg for Cabinet/Rack (Ip = 1.5 only):
 - < 1/3 h of Building Height (\$1.3a)
 - < 2/3 h of Building Height (S1.3b)
 - Top of Building Height (S1.3c)
- f. Determine cabinet detail sheet from Table 3a, 3b or 3c on Sheet S1.3a, S1.3b or S1.3c dependent on location in Bldg (Ip = 1.5 only).
- g. Determine supporting concrete type (Normal or Light Weight, f'c = 3000 psi min.)
- h. Determine anchor bolt installation parameters on sheet S3.0 & S3.1.
- 4. Engineer of Record for the building structure shall verify that governing loads indicated can be supported by the existing structure and that construction methods (i.e. embed, spacing, and edge distance) is in conformance with details.
- 5. Cabinet/Rack Anchors:
 - a. Anchors shall be:
 - 1) Hilti Kwik Bolt TZ (ICC-ES ESR-1917), carbon steel
 - 2) Simpson (ICC-ES ESR-1771)
 - 3) Powers Power Stud SD2 (ICC-ES ESR 2502)
 - b. See Tables on sheet S3.1 for applicable anchorage requirements. See S3.0 for anchorage installation instructions.
 - c. Do not drill thru existing reinforcing when installing anchors. If reinforcing is hit, notify Engineer of Record for direction.
 - d. Anchor testing special inspection (for p = 1.5 components only):
 - 1) Torque test 50% of the installed anchors as follows:

SIMPSON HILTI POWERS

1/2" Dia. – 50 ft-lbs 40 ft-lbs 40 ft-lbs

- 2) Perform test by torque wrench method. Applicable test torque must be achieved within one—half (1/2) turn of the nut.
- 3) Testing shall occur within 24 hours of anchor installation.
- 4) If any anchor fails, notify engineer of record for corrective measures.
- 5) Test equipment shall be calibrated by an approved testing laboratory in accordance with standard recognized procedures.



5-2-11

LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-FXX22, LSER-FXX27, LSER-XX22, LSER-XX27, & LSER-XX32 SEISMIC (-S) CABINET/RACK - CBC



100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400




CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012364

						Table 3a						
			Cab	inet Requireme	ents and Details	s for Cabinets i	in Lower Third	of Building He	ight			
Model			_		Maximum Cons	idered Earthqu	ake Ground Mo	tion, IBC 2009)			
Model	$S_s \leq 0.25$	$S_s \leq 0.50$	$S_s \leq 0.75$	$S_s \leq 1.00$	$S_s \leq 1.25$	$S_s \leq 1.50$	$S_s \leq 1.75$	$S_s \leq 2.00$	$S_s \leq 2.25$	$S_s \leq 2.50$	$S_s \leq 2.75$	$S_s \leq 3.00$
	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See
LSER-4422	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	Note 4
	52.0	52.0	52.0	52.0	52.0	52.8	52.8	52.9	52.9	52,10	52,10	14016 4
	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See
LSER-4022	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	Note 4
	52.0	52.0	52.0	52.0	52.0	52.5	52.5	52.5	52.6	52.7	52.7	140164
	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB
LSER-3522	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU
	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.3	52.4
	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic
LSER-2422	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)
LSER-2122	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0
	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	_	_	_	
LSER-4427	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	+EQQ-4RU	See	See	See	See
LSER-4432	52.0	52.0	52.8	52.8	52.9	52,10	52,10	52,10	Note 4	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB			
LSER-4027	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See	See
LSER-4032	52.0	52.0	52.0	52.0	52.5	52.5	52.6	52.6	52,7	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB		
LSER-3527	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See
LSER-3532	52.0	52.0	52.0	52.0	52.0	52.2	52.2	52.3	52.3	52.4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic
LSER-2427	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)				
LSER-2127	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0
	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	32.0
LSGR-4422	Cabinet (-S)	+EQQ-1RU				+EQQ-4RU	+EQQ-4RU	See				
L36K-4422	52.0		52.0	52.0		52.8	+EQQ-1RU 52.8	+EQQ-2RU	+EQQ-2RU 52.9	52,10	52.10	Note 4
		52.0 Seismic			52.0 Seismic	(-S) CAB		52.9		(-S) CAB		
1 660 4022	Seismic		Seismic	Seismic	l	` '	(-S) CAB	(-S) CAB	(-S) CAB	` '	(-S) CAB	See
LSGR-4022	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	Note 4
	52.0	52.0	52.0	52.0	52.0	52.5	S2.5	52.5	52.6	52.7	52.7	(C) CAD
1.665.3533	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB
LSGR-3522	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU
1.660.4407	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.3	52.4
LSGR-4427	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See	See	See	See
LSGR-4432	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	+EQQ-4RU	Note 4	Note 4	Note 4	Note 4
LSGR-4436	52,0	52.0	52.8	52.8	52.9	52.10	52.10	52.10				
LSGR-4027	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See	See	See
LSGR-4032	Cabinet (-5)	Cabinet (-5)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	Note 4	Note 4	Note 4
LSGR-4036	52.0	52.0	52.0	52.0	52.5	52.5	52.6	52.6	52.7			
LSGR-3527	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See	See
LSGR-3532	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	Note 4	Note 4
LSGR-3536	52.0	52.0	52.0	52.0	52.0	52.2	52.2	52.3	52.3	52.4	14010 1	14010 1
	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic
LSGR-2427	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)	Cabinet (-5)				
LOOK-LTL1	cubiner (-5)	cubine (-5)	Cabinei (-3)	cabinei (-3)	Cubiner (-5)	cubine (-5)	cabine (-3)	cabiner (3)	cabiner (3)	cabiner (3)	cubiner (-5)	cabine (-3)

¹⁾ Table is applicable to Cabinet/Racks located at one third of the height of the building and below.

⁴⁾ Lowell Cabinet/Rack model is not seismically qualified to this spectral acceleration level based on the conservative parameters used in the qualification analysis. Contact Lowell Manufacturing for possible inclusion based on specific installation conditions.





5-2-11

LOWELL PARK YES

LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-XX22, LSER-XX27, & LSER-XX32 SESMIC (-S) CABINET/RACK - CBC



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, inc 1415 Elbridge Poune Rd Suite 265 Chesterfield, MO 63017 MO COA * 2006012384

JOB NO.
CCS10-050
DATE
2 MAY 2011

S1.3a

²⁾ For Ss see 2010 CBC, Figure 1613.5 (1).

³⁾ Indicated detail sheet specifies the required installation instructions.

Table 3b												
Cabinet Requirements and Details for Cabinets in Middle Third of Building Height												
Model	Maximum Considered Earthquake Spectral Acceleration, 5s, IBC 2009											
Model	$S_s \leq 0.25$	$S_s \leq 0.50$	$S_s \leq 0.75$	$S_s \leq 1.00$	$S_s \leq 1.25$	$S_s \leq 1.50$	$S_s \leq 1.75$	$S_s \leq 2.00$	$S_s \leq 2.25$	$S_s \leq 2.50$	$S_s \leq 2.75$	$S_s \leq 3.00$
	Seismic	Seismic	Seismic	Seismic	(-S) CAB	See	See	See				
LSER-4422	Cabinet (-5)	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	Note 4	Note 4	Note 4
	52.0	52.0	52.0	52.0	52.8	52.9	52.9	52.10	52.10	1401E 4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	(-S) CAB	6	See	See				
LSER-4022	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	See Note 4		
	52.0	52.0	52.0	52.0	52.5	52.5	52.6	52.7	52.7	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	C	C				
LSER-3522	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See
	52.0	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.3	52.4	Note 4	Note 4
1.650.0400	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB
LSER-2422	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU
LSER-2122	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.1	52.1
I CED 4427	Seismic	(-S) CAB	c	c	c	6	c	c				
LSER-4427	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	See	See	See	See	See	See
LSER-4432	52.0	52.8	52.8	52.9	52.10	52.10	Note 4					
1.650.4007	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	_	-	_	_	-
LSER-4027	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	See	See	See	See	See
LSER-4032	52.0	52.0	52.0	52.5	52.5	52.6	52.7	Note 4				
1 650 3537	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	-	_	_	-
LSER-3527	Cabinet (-5)	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See	See	See
LSER-3532	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.4	Note 4	Note 4	Note 4	Note 4
1.650.0407	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB
LSER-2427	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU
LSER-2127	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.1	52.1
	Seismic	Seismic	Seismic	Seismic	(-S) CAB	_	_	-				
LSGR-4422	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	See	See	See
	52.0	52.0	52.0	52.0	52.8	52.9	52.9	52.10	52.10	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	(-S) CAB	C	C	C				
LSGR-4022	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	See Note 4	See	See
	52.0	52.0	52.0	52.0	52.5	52.5	52.6	52.7	52.7		Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	6	See				
LSGR-3522	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See Note 4	Note 4
	52.0	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.3	52.4	14016 4	14016 4
LSGR-4427	Seismic	(-S) CAB	See	See	See	See	See	See				
LSGR-4432	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	Note 4	See Note 4	See Note 4	See Note 4	See Note 4	See Note 4
LSGR-4436	52.0	52.8	52.8	52.9	52.10	52.10	INUIE 4	INUIE 4	INUIE 4	140164	INUIE 4	INUIE 4
LSGR-4027	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See	See	See	See	See
LSGR-4032	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	See Note 4				
LSGR-4036	52.0	52.0	52.0	52.5	52.5	52.6	52.7	NOTE 4				
LSGR-3527	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB	See	See	See	See
LSGR-3532	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	Note 4	See Note 4	See Note 4	
LSGR-3536	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.4	14016	17016 4	17016 4	Note 4
	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB
LSGR-2427	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU
	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.1	52.1

¹⁾ Table is applicable to Cabinet/Racks located at two thirds of the height of the building and below.

³⁾ Indicated detail sheet specifies the required installation instructions.
4) Lowell Cabinet/Rack model is not seismically qualified to this spectral acceleration level based on the conservative parameters used in the qualification analysis. Contact Lowell Manufacturing for possible inclusion based on specific installation conditions.





5-2-11

LOWELL

LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-XX22, LSER-XX27, & LSER-XX32 SESMIC (-S) CABINET/RACK - CBC

100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

²⁾ For Ss see 2010 CBC, Figure 1613.5 (1).

Table 3c

Cabinet Requirements and Details for Cabinets in Upper Third of Building Height										
	Maximum Considered Earthquake Spectral Acceleration, Ss, IBC 2009									
Model	S _s ≤ 0.25	$S_s \le 0.50$	$S_s \le 0.75$	S _s ≤ 1.00	S _s ≤ 1.25	S _s ≤ 1.50	S _s ≤ 1.75	S _s ≤ 2.00	$S_s \leq 2.25$	$S_s \le 2.50$
LSER-4422	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-5) CAB	(-S) CAB			
	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See	See
	52.0	52.0	52.0	52.8	52.9	52.9	52.10	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-5) CAB	(-5) CAB			
LSER-4022	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	See	See	See
	52.0	52.0	52.0	52.5	52.5	52.6	52.7	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-5) CAB	(-5) CAB	(-S) CAB		
LSER-3522	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See
	52.0	52.0	52.0	52.0	52.2	52.3	52.3	52.4	Note 4	Note 4
	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-5) CAB
LSER-2422	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	Cabinet (-5)	+EQQ-1RU	+EQQ-1RU
LSER-2122	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.0	52.1	52,1
	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB					
LSER-4427	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-4RU	+EQQ-4RU	See	See	See	See	See
LSER-4432	52.0	52.8	52.9	52.10	52.10	Note 4	Note 4	Note 4	Note 4	Note 4
	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	(-S) CAB				
LSER-4027	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU	+EQQ-4RU	See	See	See	See
LSER-4032	52.0	52.0	52.5	52.6	52.6	52.7	Note 4	Note 4	Note 4	Note 4
	Seismic	Seismic	Seismic	(-S) CAB	(-S) CAB	(-S) CAB	See See			
LSER-3527	Cabinet (-S)	Cabinet (-S)	Cabinet (-S)	+EQQ-1RU	+EQQ-2RU	+EQQ-2RU			See	See Note 4
LSER-3532	52.0	52.0	52.0	52.2	52.3	52.3	Note 4	Note 4	Note 4	
L CED 2427	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	Seismic	(-S) CAB	(-5) CAB
LSER-2427	Seismic Cabinet (-S)	Seismic Cabinet (-S)	Seismic Cabinet (-S)	Seismic Cabinet (-S)	Seismic Cabinet (-S)		Seismic Cabinet (-S)	Seismic Cabinet (-S)	(-S) CAB +EQQ-1RU	(-S) CAB +EQQ-1RU
LSER-2427 LSER-2127						Seismic				
	Cabinet (-S)	Cabinet (-5)	Cabinet (-5)	Cabinet (-S)	Cabinet (-S)	Seismic Cabinet (-S)	Cabinet (-5)	Cabinet (-S) 52.0	+EQQ-1RU 52.1	+EQQ-1RU 52,1
	Cabinet (-5) 52.0	Cabinet (-5) 52.0	Cabinet (-5) 52.0	Cabinet (-5) S2.0	Cabinet (-5) 52.0	Seismic Cabinet (-S) 52.0	Cabinet (-5) 52.0	Cabinet (-S) 52.0 See	+EQQ-1RU 52.1 See	+EQQ-1RU 52.1 See
LSER-2127	Cabinet (-S) S2.0 Seismic	Cabinet (-S) 52,0 Seismic	Cabinet (-S) 52,0 Seismic	Cabinet (-S) 52,0 (-S) CAB	Cabinet (-S) 52,0 (-S) CAB	Seismic Cabinet (-S) S2.0 (-S) CAB	Cabinet (-S) 52,0 (-S) CAB	Cabinet (-S) 52.0	+EQQ-1RU 52.1	+EQQ-1RU 52,1
LSER-2127	Cabinet (-5) 52.0 Seismic Cabinet (-5)	Cabinet (-S) 52.0 Seismic Cabinet (-S)	Cabinet (-S) S2.0 Seismic Cabinet (-S)	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU	Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU	Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU	Cabinet (-5) 52.0 See Note 4	+EQQ-1RU 52.1 See Note 4	+EQQ-1RU 52.1 See Note 4
LSER-2127	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0	Cabinet (-S) 52.0 Seismic Cabinet (-S) 52.0	Cabinet (-S) 52.0 Seismic Cabinet (-S) 52.0	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9	Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9	Cabinet (-5) 52.0 (-5) CAB +EQQ-4RU 52.10	Cabinet (-5) 52.0 See Note 4	+EQQ-1RU 52.1 See Note 4	+EQQ-1RU 52.1 See Note 4
LSER-2127 LSGR-4422	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB	Cabinet (-5) 52.0 (-5) CAB +EQQ-2RU 52.9 (-5) CAB	Seismic Cabinet (-5)	Cabinet (-5) 52.0 (-5) CAB +EQQ-4RU 52.10 (-5) CAB	Cabinet (-5) 52.0 See Note 4	+EQQ-1RU 52.1 See Note 4	+EQQ-1RU 52.1 See Note 4
LSER-2127 LSGR-4422	Cabinet (-5) S2.0 Seismic Cabinet (-5) S2.0 Seismic Cabinet (-5)	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic Cabinet (-5)	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic Cabinet (-5)	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU	Cabinet (-5) 52.0 (-5) CAB +EQQ-2RU 52.9 (-5) CAB +EQQ-1RU	Seismic Cabinet (-S)	Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU	Cabinet (-5) 52.0 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4
LSER-2127 LSGR-4422	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0	Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0 Seismic Cabinet (-5) 52.0	Cabinet (-5) 52.0 (-5) CAB +EQQ-1RU 52.8 (-5) CAB +EQQ-1RU 52.5	Cabinet (-5) 52.0 (-5) CAB +EQQ-2RU 52.9 (-5) CAB +EQQ-1RU 52.5	Seismic Cabinet (-S)	Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.7	Cabinet (-S) S2.0 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4	+EQQ-1RU 52.1 5ee Note 4 See Note 4
LSER-2127 LSGR-4422 LSGR-4022	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-S) 52.0 Seismic Cabinet (-S) 52.0 Seismic Cabinet (-S) 52.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic S2.0 Seismic	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB	Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-2RU S2.6 (-S) CAB	Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.7 (-S) CAB	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB	+EQQ-1RU 52.1 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4
LSER-2127 LSGR-4422 LSGR-4022	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic Cabinet (-S)	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB +EQQ-1RU	Seismic Cabinet (-5) 52.0 (-5) CAB +EQQ-2RU 52.9 (-5) CAB +EQQ-2RU 52.6 (-5) CAB +EQQ-2RU 52.3	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4
LSER-2127 LSGR-4422 LSGR-4022 LSGR-3522	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic Cabinet (-S) 52.0	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB +EQQ-1RU 52.2	Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-2RU 52.6 (-S) CAB +EQQ-2RU 52.3 See	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4	+EQQ-1RU S2.1 See Note 4 See Note 4 See Note 4
LSGR-4422 LSGR-4022 LSGR-3522 LSGR-4427	Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic Cabinet (-S) 52.0 (-S) CAB	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB +EQQ-1RU 52.2 (-S) CAB	Seismic Cabinet (-5) 52.0 (-5) CAB +EQQ-2RU 52.9 (-5) CAB +EQQ-2RU 52.6 (-5) CAB +EQQ-2RU 52.3	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4
LSGR-4422 LSGR-4022 LSGR-3522 LSGR-4427 LSGR-4432 LSGR-4436 LSGR-4027	Cabinet (-S) S2.0 Seismic Cabinet (-S) Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB	Cabinet (-S) \$2.0 (-S) CAB +EQQ-1RU \$2.8 (-S) CAB +EQQ-1RU \$2.5 Seismic Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB	Cabinet (-S) \$2.0 (-S) CAB +EQQ-2RU \$2.9 (-S) CAB +EQQ-1RU \$2.5 (-S) CAB +EQQ-1RU \$2.2 (-S) CAB +EQQ-4RU \$2.2 (-S) CAB (-S) CAB (-S) CAB	Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-2RU S2.6 (-S) CAB +EQQ-2RU S2.3 See Note 4 (-S) CAB	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4
LSGR-4422 LSGR-4022 LSGR-3522 LSGR-4427 LSGR-4436 LSGR-4027 LSGR-4032	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9	Cabinet (-S) \$2.0 (-S) CAB +EQQ-1RU \$2.8 (-S) CAB +EQQ-1RU \$2.5 Seismic Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10	Cabinet (-S) \$2.0 (-S) CAB +EQQ-2RU \$2.9 (-S) CAB +EQQ-1RU \$2.5 (-S) CAB +EQQ-1RU \$2.2 (-S) CAB +EQQ-1RU \$2.2	Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-2RU 52.6 (-S) CAB +EQQ-2RU 52.3 See Note 4 (-S) CAB +EQQ-4RU	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4 See	+EQQ-1RU S2.1 See Note 4 See	+EQQ-1RU S2.1 See Note 4 See
LSGR-4422 LSGR-4022 LSGR-4427 LSGR-4427 LSGR-4432 LSGR-4436 LSGR-4027 LSGR-4032 LSGR-4032 LSGR-4036	Cabinet (-S) S2.0 Seismic Cabinet (-S) Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic Cabinet (-S) S2.0	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-2RU 52.6	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB +EQQ-4RU 52.2 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.10	Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-2RU S2.6 (-S) CAB +EQQ-2RU S2.3 See Note 4 (-S) CAB +EQQ-4RU S2.7	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4
LSGR-4422 LSGR-4022 LSGR-4022 LSGR-4427 LSGR-4432 LSGR-4436 LSGR-4032 LSGR-4036 LSGR-4036	Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.8 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-1RU S2.5 Seismic	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.10 (-S) CAB (-S) CAB (-S) CAB (-S) CAB	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-2RU 52.10 (-S) CAB (-S) CAB	Seismic Cabinet (-5) S2.0 (-5) CAB +EQQ-2RU S2.9 (-5) CAB +EQQ-2RU S2.6 (-5) CAB +EQQ-2RU S2.3 See Note 4 (-5) CAB +EQQ-4RU S2.7 (-5) CAB	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4 See Note 4	+EQQ-1RU 52.1 See Note 4 See Note 4 See Note 4 See Note 4	+EQQ-1RU S2.1 See Note 4
LSGR-4422 LSGR-4022 LSGR-4022 LSGR-4427 LSGR-4432 LSGR-4036 LSGR-4036 LSGR-4036 LSGR-3527 LSGR-3532	Cabinet (-S) S2.0 Seismic Cabinet (-S)	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-1RU S2.5 Seismic Cabinet (-S)	Cabinet (-S) 52.0 (-S) CAB +EQQ-1RU 52.8 (-S) CAB +EQQ-1RU 52.5 Seismic Cabinet (-S) 52.0 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-2RU 52.6 (-S) CAB +EQQ-2RU 52.6 (-S) CAB +EQQ-1RU	Cabinet (-S) 52.0 (-S) CAB +EQQ-2RU 52.9 (-S) CAB +EQQ-1RU 52.5 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-4RU 52.10 (-S) CAB +EQQ-2RU 52.6 (-S) CAB +EQQ-2RU	Seismic Cabinet (-5) S2.0 (-5) CAB +EQQ-2RU S2.9 (-5) CAB +EQQ-2RU S2.6 (-5) CAB +EQQ-2RU S2.3 See Note 4 (-5) CAB +EQQ-4RU S2.7 (-5) CAB +EQQ-4RU	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4 See Note 4	+EQQ-1RU S2.1 See Note 4	+EQQ-1RU S2.1 See Note 4
LSGR-4422 LSGR-4022 LSGR-4022 LSGR-4427 LSGR-4432 LSGR-4436 LSGR-4032 LSGR-4036 LSGR-4036	Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-1RU S2.5 Seismic	Cabinet (-S) \$2.0 (-S) CAB +EQQ-1RU \$2.8 (-S) CAB +EQQ-1RU \$2.5 Seismic Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-2RU \$2.6	Cabinet (-S) \$2.0 (-S) CAB +EQQ-2RU \$2.9 (-S) CAB +EQQ-1RU \$2.5 (-S) CAB +EQQ-1RU \$2.2 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-2RU \$2.6	Seismic Cabinet (-5) S2.0 (-5) CAB +EQQ-2RU S2.9 (-5) CAB +EQQ-2RU S2.6 (-5) CAB +EQQ-2RU S2.3 See Note 4 (-5) CAB +EQQ-4RU S2.7 (-5) CAB +EQQ-4RU S2.7 (-5) CAB +EQQ-4RU S2.7	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4 See Note 4	+EQQ-1RU S2.1 See Note 4	+EQQ-1RU S2.1 See Note 4
LSER-2127 LSGR-4422 LSGR-4022 LSGR-3522 LSGR-4436 LSGR-4036 LSGR-4036 LSGR-3532 LSGR-3536	Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-1RU S2.5 Seismic Cabinet (-S) Seismic	Cabinet (-S) \$2.0 (-S) CAB +EQQ-1RU \$2.8 (-S) CAB +EQQ-1RU \$2.5 Seismic Cabinet (-S) \$2.0 (-S) CAB +EQQ-2RU \$2.10 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-1RU \$2.2 Seismic	Cabinet (-S) \$2.0 (-S) CAB +EQQ-2RU \$2.9 (-S) CAB +EQQ-1RU \$2.5 (-S) CAB +EQQ-4RU \$2.2 (-S) CAB +EQQ-2RU \$2.10 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB *EQQ-2RU \$2.6 (-S) CAB *EQQ-2RU \$2.6 (-S) CAB *EQQ-2RU \$2.6 (-S) CAB	Seismic Cabinet (-5) S2.0 (-5) CAB +EQQ-2RU S2.9 (-5) CAB +EQQ-2RU S2.6 (-5) CAB +EQQ-2RU S2.3 See Note 4 (-5) CAB +EQQ-4RU S2.7 (-5) CAB +EQQ-4RU S2.7 S2.7 S2.3 Seismic	Cabinet (-S)	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4 See Note 4 See Note 4 See Note 4	+EQQ-1RU S2.1 See Note 4 Companies to the first term of the firs	+EQQ-1RU S2.1 See Note 4 C-See Note 4
LSGR-4422 LSGR-4022 LSGR-4022 LSGR-4427 LSGR-4432 LSGR-4036 LSGR-4036 LSGR-4036 LSGR-3527 LSGR-3532	Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-1RU S2.8 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic	Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 Seismic Cabinet (-S) S2.0 (-S) CAB +EQQ-2RU S2.9 (-S) CAB +EQQ-1RU S2.5 Seismic Cabinet (-S) S2.5 Seismic	Cabinet (-S) \$2.0 (-S) CAB +EQQ-1RU \$2.8 (-S) CAB +EQQ-1RU \$2.5 Seismic Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-2RU \$2.6	Cabinet (-S) \$2.0 (-S) CAB +EQQ-2RU \$2.9 (-S) CAB +EQQ-1RU \$2.5 (-S) CAB +EQQ-1RU \$2.2 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-2RU \$2.6 (-S) CAB +EQQ-2RU \$2.6	Seismic Cabinet (-5) S2.0 (-5) CAB +EQQ-2RU S2.9 (-5) CAB +EQQ-2RU S2.6 (-5) CAB +EQQ-2RU S2.3 See Note 4 (-5) CAB +EQQ-4RU S2.7 (-5) CAB +EQQ-4RU S2.7 (-5) CAB +EQQ-4RU S2.7	Cabinet (-S) \$2.0 (-S) CAB +EQQ-4RU \$2.10 (-S) CAB +EQQ-4RU \$2.7 (-S) CAB +EQQ-2RU \$2.3 See Note 4 See Note 4	Cabinet (-S) S2.0 See Note 4 See Note 4 (-S) CAB +EQQ-4RU S2.4 See Note 4 See Note 4	+EQQ-1RU S2.1 See Note 4	+EQQ-1RU S2.1 See Note 4

h -2h/3 h/3



LOWELL

LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-XX22, LSER-XX27, & LSER-XX32 SESMIC (-S) CABINET/RACK - CBC




100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA * 2006012384

¹⁾ Table is applicable to Cabinet/Racks located at the roof and below.
2) For Ss see 2010 CBC, Figure 1613.5 (1).
3) Indicated detail sheet specifies the required installation instructions.
4) Lowell Cabinet/Rack model is not seismically qualified to this spectral acceleration level based on the conservative parameters used in the qualification analysis. Contact Lowell Manufacturing for possible inclusion based on specific installation conditions.



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-XX22, LSER-XX27, & LSER-XX32 SEISMIC (-S) CABINET/RACK CBC QUALIFIED




100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO.
CCS10-050
DATE
2 MAY 2011
S2.0



I) REFER TO SHEET SI.3a, SI.3b, or SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL


LSGR-2427, LSER-2422, LSER-2427 LSER-2122, LSER-2127 SEISMIC (-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, or SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL


LSGR-2427, LSER-2422, LSER-2427 LSER-2122, LSER-2127 SEISMIC (-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL

LSGR-3522, LSGR-3527, LSGR-3532, LSGR-3536, LSER-3522, LSER-3527, & LSER-3532 SEISMIC


(-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL

LSGR-3522, LSGR-3527, LSGR-3532, LSGR-3536, LSER-3522, LSER-3527, & LSER-3532 SEISMIC (-S) CABINET/RACK


+ EQQ-1RU BRACE - CBC QUALIFIED

Lowell

100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



NOTES: I) REFER TO SHEET SI.3a, SI.3b, or SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-3522, LSGR-3527, LSGR-3532, LSGR-3536, LSER-3522, LSER-3527, & LSER-3532 SEISMIC (-S) CABINET/RACK + EQQ-2RU BRACE - CBC QUALIFIED

Lowell

100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA * 2006012384



I) REFER TO SHEET SI.3a, SI.3b, or SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-3522, LSGR-3527, LSGR-3532, LSGR-3536, LSER-3522, LSER-3527, & LSER-3532

SEISMIC (-S) CABINET/RACK + EQQ-2RU BRACE - CBC QUALIFIED

100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



NOTES:
1) REFER TO SHEET SI.3a, SI.3b, or SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-3522, LSGR-3527, LSGR-3532, LSGR-3536, LSER-3522, LSER-3527, & LSER-3532 SEISMIC (-S) CABINET/RACK + EQQ-4RU BRACE - CBC QUALIFIED Lowell

100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO. CCS10-050 DATE 2 MAY 2011 S2.40



I) REFER TO SHEET SI.3a, SI.3b, or SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL

LSGR-3522, LSGR-3527, LSGR-3532, LSGR-3536, LSER-3522, LSER-3527, & LSER-3532 SEISMIC (-S) CABINET/RACK + EQQ-4RU BRACE - CBC QUALIFIED




100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO. CCS10-050 DATE 2 MAY 2011 S2.46



NOTES:
1) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-4022, LSGR-4027, LSGR-4032, LSGR-4036, LSER-4022, LSER-4027, & LSER-4032 SEISMIC (-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-4022, LSGR-4027, LSGR-4032, LSGR-4036, LSER-4022, LSER-4027, & LSER-4032 SEISMIC (-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED

Lowell

100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



NOTES: I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL

LSGR-4022, LSGR-4027, LSGR-4032, LSGR-4036, LSER-4022, LSER-4027, LSER-4032

SEISMIC (-S) CABINET/RACK
+ EQQ-2RU BRACE - CBC QUALIFIED




100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO. CCS10-050 DATE 2 MAY 2011 S2.60



NOTES: I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL

LSGR-4022, LSGR-4027, LSGR-4032, LSGR-4036, LSER-4022, LSER-4027, LSER-4032 SEISMIC (-S) CABINET/RACK + EQQ-2RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400




CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO.

CCS10-050

DATE
2 MAY 2011

\$2.66



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL


LSGR-4022, LSGR-4027, LSGR-4032, LSGR-4036, LSER-4022, LSER-4027, & LSER-4032 SEISMIC (-S) CABINET/RACK + EQQ-4RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-4022, LSGR-4027, LSGR-4032, LSGR-4036, LSER-4022, LSER-4027, & LSER-4032 SEISMIC (-S) CABINET/RACK + EQQ-4RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL

LSGR-4422, LSGR-4427, LSGR-4432, LSGR-4436, LSER-4422, LSER-4427, & LSER-4432 SEISMIC (-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED




100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO. CCS10-050 DATE 2 MAY 2011 S2.8a



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL

LSGR-4422, LSGR-4427, LSGR-4432, LSGR-4436, LSER-4422, LSER-4427, & LSER-4432 SEISMIC (-S) CABINET/RACK + EQQ-1RU BRACE - CBC QUALIFIED




100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA * 2006012384

JOB NO.
CCS10-050
DATE
2 MAY 2011
S2.86



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL


LSGR-4422, LSGR-4427, LSGR-4432, LSGR-4436, LSER-4422, LSER-4427, & LSER-4432 SEISMIC (-S) CABINET/RACK + EQQ-2RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11

LOWELL

LSGR-4422, LSGR-4427, LSGR-4432, LSGR-4436, LSER-4422, LSER-4427, & LSER-4432 SEISMIC (-S) CABINET/RACK + EQQ-2RU BRACE - CBC QUALIFIED




100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Poune Rd Suite 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO. CCS10-050 DATE 2 MAY 2011 S2.9b



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



LOWELL


LSGR-4422, LSGR-4427, LSGR-4432, LSGR-4436, LSER-4422, LSER-4427, & LSER-4432 SEISMIC (-S) CABINET/RACK + EQQ-4RU BRACE - CBC QUALIFIED



100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



1415 Elbridge Payne Rd Sulte 265 Chesterfield, MO 63017 MO COA # 2006012384



I) REFER TO SHEET SI.3a, SI.3b, OR SI.3c FOR COMPLETE MODEL NO. APPLICABILITY.



5-2-11


LOWELL

LSGR-4422, LSGR-4427, LSGR-4432, LSGR-4436, LSER-4422, LSER-4427, & LSER-4432 SEISMIC (-S) CABINET/RACK + EQQ-4RU BRACE - CBC QUALIFIED

100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Suite 265 Chesterfield, MO 63017 MO COA * 2006012384





5-2-11

LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-FXX22, LSER-FXX27, LSER-XX22, LSER-XX27, & LSER-XX32 SEISMIC (-S) CABINET/RACK - CBC




100 Integram Drive Pacific, MO 63069 Phone (636) 257—3400



CCS Group, Inc 1415 Elbridge Payne Rd Sulte 265 Chesterfield, MO 63017 MO COA # 2006012384

JOB NO. CCS10-050 DATE 2 MAY 2011

S3.0a





5-2-11

LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-FXX22, LSER-FXX27, LSER-XX22, LSER-XX27, & LSER-XX32 SEISMIC (-S) CABINET/RACK - CBC

100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400

CCS Group, inc 1415 Elbridge Poune Rd Suite 265 Chesterfield, MO 63017 MO COA * 2006012384

TABLE 4 - LIFE SAFETY/ESSENTIAL SYSTEM ANCHORAGE REQUIREMENTS (Ip = 1.5)

ANCHOR TYPE	NOMINAL EMBEDMENT	WASHER	MIN SLAB DEPTH	MIN EDGE DISTANCE
½Φ HILTI KWIK BOLT TZ	3 3 "	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	2 3 "
½Φ SIMPSON STRONG BOLT	3 7 "	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	4"
¹ Φ POWERS POWER STUD SD2	3 3 4	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	4"

- I) APPLIES TO NORMAL AND LIGHTWEIGHT CONCRETE
- 2) Wp AND CONTENT WEIGHT PER TABLE I ON SHEET SI.O
- 3) lp = 1.5 ONLY

TABLE 5 - TYPICAL INSTALLATION ANCHORAGE REQUIREMENTS (Ip = 1.0)

CONRETE TYPE	ANCHOR TYPE	MAX Ss	NOMINAL EMBEDMENT	WASHER	MIN SLAB DEPTH	MIN EDGE DISTANCE
NORMAL WEIGHT CONCRETE	½0" HILTI KWIK BOLT TZ		3 <u>3</u> 4	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	2 3 "
	½Φ" SIMPSON STRONG BOLT	3.00	3] "	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	4"
	½ [†] " POWERS POWER STUD SD2		3 <u>3</u> "	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	4"
LIGHT WEIGHT CONCRETE	½0" HILTI KWIK BOLT TZ	2.50	3 <u>3</u> 4	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	5"
	½Φ" SIMPSON STRONG BOLT	2.00	3 7 "	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	5"
	¹ / ₂ Φ" POWERS POWER STUD SD2	2.50	3 3 "	$1\frac{1}{2}$ " $\times \frac{1}{8}$ "	6"	5"

1) Wp = 1500 lb, 1200 lb CONTENTS

2) lp = 1.0 ONLY



5-2-11

LOWELL LSGR-XX22, LSGR-XX27, LSGR-XX32, LSGR-XX36, LSER-FXX22, LSER-FXX27, LSER-XX22, LSER-XX27, & LSER-XX32

SEISMIC (-S) CABINET/RACK - CBC

Lowell

100 Integram Drive Pacific, MO 63069 Phone (636) 257-3400



JOB NO. CCS10-050 DATE 2 MAY 2011

CCS Group, Inc I4I5 Elbridge Payne Rd Sulte 265 Chestrefield, Mo 63017 MO COA # 2006012384